

Reverse Equalizer, 65 MHz -FAST-PAC™



For Broadband International FAST-PAC™ Amplifier Products

| PARAMETER | SPECIFICATION | Unit |
|----------------------|---------------|------|
| Passband | 5-65 | MHz |
| Flatness | +/- 0.3 | dB |
| Insertion Loss (Max) | 1 | dB |
| Return Loss | -18 | dB |

65 MHz Slope Chart – Frequency vs. Insertion Loss

| OEM Part Number | BBI Part Number | Value | Slope | 5 | 65 |
|-----------------|-----------------|-------|-------|-----|----|
| 21E000 | 21E000 | 0 dB | 0 | 0 | 0 |
| 21E601R | 21E601R | 1 dB | 0.8 | 1.3 | .5 |
| 21E602R | 21E602R | 2 dB | 1.5 | 2.0 | .5 |
| 21E603R | 21E603R | 3 dB | 2.3 | 2.8 | .5 |
| 21E604R | 21E604R | 4 dB | 3.1 | 3.6 | .5 |
| 21E605R | 21E605R | 5 dB | 3.8 | 4.3 | .5 |
| 21E606R | 21E606R | 6 dB | 4.6 | 5.1 | .5 |
| 21E607R | 21E607R | 7 dB | 5.4 | 5.9 | .5 |
| 21E608R | 21E608R | 8 dB | 6.1 | 6.6 | .5 |
| 21E609R | 21E609R | 9 dB | 6.9 | 7.4 | .5 |
| 21E610R | 21E610R | 10 dB | 7.7 | 8.2 | .5 |
| 21E611R | 21E611R | 11 dB | 8.4 | 8.9 | .5 |
| 21E612R | 21E612R | 12 dB | 9.2 | 9.7 | .5 |