



Attenuator Pad, 9A, w/ cover

For ARRIS[®], C-COR[®], Philips[®]/Magnavox[®] Amplifiers

| PRODUCT SPECIFICATIONS | | |
|------------------------|-----------------|----------------|
| Parameter | Unit of Measure | Specifications |
| Bandwidth | MHz | 5 -1003 MHz |
| Attenuation@ 5 MHz | dB | +/- 0.20 |
| Attenuation@ 1003 MHz | dB | +/- 0.35 |
| Return Loss (MIN) | dB | -22 |

| OEM P.N. | BBI P.N. | Values | OEM P.N. | BBI P.N. | Values |
|-----------|----------|---------|-----------|----------|---------|
| 2500505WC | 451900WC | 0 dB | 2500715WC | 451913WC | 13 dB |
| 9A-WC-05 | 451500WC | .5 dB | 9A-WC-135 | 451513WC | 13.5 dB |
| 2500856WC | 451901WC | 1 dB | 2500717WC | 451914WC | 14 dB |
| 9A-WC-15 | 451501WC | 1.5 dB | 9A-WC-145 | 451514WC | 14.5 dB |
| 2500857WC | 451902WC | 2 dB | 2500864WC | 451915WC | 15 dB |
| 9A-WC-25 | 451502WC | 2.5 dB | 9A-WC-155 | 451515WC | 15.5 dB |
| 2500858WC | 451903WC | 3 dB | 2500720WC | 451916WC | 16 dB |
| 9A-WC-35 | 451503WC | 3.5 dB | 9A-WC-165 | 451516WC | 16.5 dB |
| 2500859WC | 451904WC | 4 dB | 2500722WC | 451917WC | 17 dB |
| 9A-WC-45 | 451504WC | 4.5 dB | 9A-WC-175 | 451517WC | 17.5 dB |
| 2500860WC | 451905WC | 5 dB | 2500865WC | 451918WC | 18 dB |
| 9A-WC-55 | 451505WC | 5.5 dB | 9A-WC-185 | 451518WC | 18.5 dB |
| 2500861WC | 451906WC | 6 dB | 2500725WC | 451919WC | 19 dB |
| 9A-WC-65 | 451506WC | 6.5 dB | 9A-WC-195 | 451519WC | 19.5 dB |
| 2500705WC | 451907WC | 7 dB | 2502005WC | 451920WC | 20 dB |
| 9A-WC-75 | 451507WC | 7.5 dB | 9A-WC-205 | 451520WC | 20.5 dB |
| 2500707WC | 451908WC | 8 dB | 2502105WC | 451921WC | 21 dB |
| 9A-WC-85 | 451508WC | 8.5 dB | 9A-WC-215 | 451521WC | 21.5 dB |
| 2500862WC | 451909WC | 9 dB | 2502205WC | 451922WC | 22 dB |
| 9A-WC-95 | 451509WC | 9.5 dB | 2502305WC | 451923WC | 23 dB |
| 2500710WC | 451910WC | 10 dB | 2502405WC | 451924WC | 24 dB |
| 9A-WC-105 | 451510WC | 10.5 dB | 2502505WC | 451925WC | 25 dB |
| 2500712WC | 451911WC | 11 dB | 2507505WC | 451875WC | 75 ohm |