

# Reverse Equalizer, 85 MHz -FAST-PAC™



## For Broadband International FAST-PAC™ Amplifier Products

PARAMETER	SPECIFICATION	Unit
Passband	5-85	MHz
Flatness	+/- 0.3	dB
Insertion Loss (Max)	1	dB
Return Loss	-18	dB

### 85 MHz Slope Chart – Frequency vs. Insertion Loss

OEM Part Number	BBI Part Number	Value	Slope	5	42	65	85
21E000	21E000	0 dB	0	0	0	0	0
21E801R	21E801R	1 dB	0.8	1.3	0.8	0.6	0.5
21E802R	21E802R	2 dB	1.5	2.0	1.2	0.8	0.5
21E803R	21E803R	3 dB	2.3	2.8	1.4	0.9	0.5
21E804R	21E804R	4 dB	3.1	3.6	1.7	1.0	0.5
21E805R	21E805R	5 dB	3.8	4.3	2.0	1.2	0.5
21E806R	21E806R	6 dB	4.6	5.1	2.4	1.3	0.5
21E807R	21E807R	7 dB	5.4	5.9	2.7	1.4	0.5
21E808R	21E808R	8 dB	6.1	6.6	3.0	1.6	0.5
21E809R	21E809R	9 dB	6.9	7.4	3.3	1.7	0.5
21E810R	21E810R	10 dB	7.7	8.2	3.6	1.8	0.5
21E811R	21E811R	11 dB	8.4	8.9	3.9	1.9	0.5
21E812R	21E812R	12 dB	9.2	9.7	4.2	2.1	0.5