

# Bode Equalizer



## For Motorola® System Amplifiers and Line Extenders

PARAMETER	SPECIFICATION	Unit
Passband	50-600, 750, 870, 1000	MHz
Flatness	+/- 0.25	dB
Values	600, 750, 870, 1000 MHz	dB
Return Loss	>18	dB

OEM P.N.	BBI P.N.	Values
Bode 600	360600	600 MHz
Bode 750	360750	750 MHz
Bode 870	360870	870 MHz
Bode 1000	360100	1000 MHz